

CMG-40TD



Broadband Seismometer and Digitiser

The Guralp Systems CMG-40TD is a rugged and robust three-component broadband seismometer with an on-board DM24 digitiser. It is ideally suited for installation in vaults with moderate noise.

Key Features:

True broadband force-feedback instrument

Four low noise 24 bit digital outputs.

Self-contained in a waterproof steel case with fully adjustable levelling feet

No mass clamping required – plug in and go

High sensitivity and dynamic range

Standard response of 30 seconds to 50 Hertz.
Options of 1, 10, 30 or 60 seconds for the long period corner and 50 or 100 Hertz for the high frequency corner

High-gain feedback loop eliminates mechanical non-linearity (the overall measured linearity exceeds 90 dB) and minimizes resonances in the spring system.

Low-frequency vibration modes are carefully avoided in the design. The lowest spurious vibration mode of the 40T is a barely measurable resonance at 440 Hz.



Specifications

CMG-40TD



Velocity output bandwidth	<i>30 seconds – 50 Hertz (Standard) 1s, 2s, 10s or 60s long period options 100Hz high frequency option</i>
Velocity output sensitivity	<i>2 × 400 V/ms⁻¹ (Standard) Options for 2 × 1000 or 2 × 1600 V/ms⁻¹ Optional high-gain output (× 10)</i>
Peak output	<i>±10 V (20 V peak-to-peak)</i>
Optional high gain sensitivity	<i>2 × 10000 V/ms⁻¹ (adjustable)</i>
Lowest spurious resonance	<i>450 Hz</i>
Linearity	<i>> 90 dB</i>
Cross-axis rejection	<i>> 65 dB</i>
Electronics noise level	<i>−172 dB (relative to 1m²s⁻⁴Hz⁻¹)</i>
Operating temperature range	<i>−20 to +75 °C</i>
Temperature sensitivity	<i>< 0.6 V per 10 °C</i>
Mass recentring range	<i>±3 ° from horizontal</i>
Materials	<i>Stainless steel case Gold plated contacts O-ring seals throughout</i>
Case diameter	<i>154 mm</i>
Case height (with handle)	<i>207 mm</i>
Weight	<i>2.49 kg</i>
Power supply	<i>10 – 36 V DC</i>
Optional low power sensor	<i>5 V DC supply (output ±4.5 V)</i>
Current at 12 V DC	<i>38 mA</i>
Calibration controls	<i>Common signal & enable lines exposed on sensor connector</i>
Offset zeroing	<i>Adjustable through case</i>
Optional remote control	<i>Offset zeroing with DC motors</i>
Optional accessories	<i>Handheld Control Unit</i>

